

# XCHCOM

## Chicago-Approved Steel LED Combo Exit Sign

The XCHCOM exit sign and emergency combination is constructed of durable 20-gauge steel and meets the City of Chicago exit sign requirements. The long-life, high-brightness LEDs ensure reliable performance and clear visibility.



### CONSTRUCTION

- Single or double face configuration
- Universal K/O pattern on back plate for wall mount
- Durable 20-gauge steel construction
- White or black finish
- Mounting canopy included for top or end mount

### ELECTRICAL

- Dual 120/277 voltage standard
- Charge rate/power "ON" LED indicator light and push-to-test switch for mandated code compliance testing
- 6V sealed lead acid, maintenance-free, rechargeable battery
- Internal solid-state transfer switch automatically connects the internal battery to LED board and LED lamp heads for minimum 120 minute emergency illumination
- Fully automatic solid-state, two rate charger initiates battery charging to recharge a discharged battery in 24 hours

- LVD (low voltage disconnect) prevents battery from deep discharge
- Remote capacity option available

### ILLUMINATION

- Long lasting, energy efficient white LED exit sign illumination
- Two 6V 5.3W adjustable white LED lamp heads

### CERTIFICATION

- Meets UL924, NFPA 101 Life Safety Code, NEC, OSHA, Local and State Codes
- UL Listed for damp locations (20°C to 50°C)

### WARRANTY

- 5 year warranty on all electronics and housing - view complete warranty terms online at [www.evenlite.com/terms-warranty](http://www.evenlite.com/terms-warranty).
- Battery pro rated for 2 years

### ORDERING GUIDE

XCHCOM-1-R-W-3

MODEL	FACE COUNT		LETTER COLOR		HOUSING COLOR	
XCHCOM	1	Single	R	Red	W	White
	2	Double				
XCHCOM			R		W	
LEGEND CODE				OPTIONS		ORDERING NOTES
SINGLE FACE		DOUBLE FACE		RC	Remote Capacity <sup>4</sup>	
3	Exit (No Arrow)	2	Stairs (No Arrow)	18	Exit (No Arrow)	1 120 minutes 2 Single face only 3 Double face only 4 6 Volts, 10 Watts
6	Exit (Right Arrow) <sup>2</sup>	5	Stairs (Right Arrow) <sup>2</sup>	21	Exit (Right/Left Arrow) <sup>3</sup>	
9	Exit (Left Arrow) <sup>2</sup>	8	Stairs (Left Arrow) <sup>2</sup>	24	Exit (Double Arrow)	
12	Exit (Double Arrow)	11	Stairs (Double Arrow)	17	Stairs (No Arrows)	
				20	Stairs (Right/Left Arrow) <sup>3</sup>	
				23	Stairs (Double Arrow)	
				B	Black Housing & Heads	

Fill in fields from categories above and complete type and part number.

Type No:	Full Part No:
----------	---------------

**DIMENSIONS**

